## MSRP: \$150.00 USD

5 + 5 WATT MIXER - AMPLIFIER

## **MA254**







The new MA254 is a compact class D stereo amplifier with a 4 CH, stereo mixer built in. It has 5 watts per channel @ 4 Ohms. The class D low heat design gives the MA254 the ability to be mounted in very tight applications. It will work great in ceilings by projectors, or anywhere small and heat free amplification is required. The MA254 is built in an all metal chassis and weighs 1 pound. Overall dimension are 6.75" X 3.5" X 1.5". Bottom mounts are provided for permanent installations. The MA254 has an included 12 VAC external power supply. The 4 channel mixer section consists of 4 separate RCA stereo inputs, along with a 3.5mm (1/8") stereo input perfect for an ipod or laptop computer type input.

## **SPECIFICATIONS**

Line Input Impedance: 10K Ohms Power Output: 5 watts X 2 @ 4 Ohms. Voltage Gain: 30 dB Maximum Supply Voltage: 24 VDC .05% typical THD: Efficiency: 85% 20Hz - 25 kHz Bandwidth: 6.75" x 3.5" x 1.5" Size: Weight:

ROLLS

MIXER - AMP

5 + 5 Watts

INSTALLATION MIX - AMPLIFIER

STEREO INPUTS AND OUTPUTS

ROLLS

5968 SOUTH 350 WEST S.L.C., UT 84107

PHONE: 801-263-9053

FAX: 801-236-9068

DATA SHEET FOR MA254

Size: 6.75" X 3.5" X 1.5"



Included - 12 VAC ROLLS PS12 external power supply

\*Optional PS242 power supply available for 15 Watts per channel.





www.rolls.com