



The RM74 MixMate 2 is six channel, single rack space, electronic audio mixer with two microphone inputs and four stereo line inputs. The unit is ideal for installs such as small restaurants or night clubs where space is a consideration, without compromising audio quality. A convenient front-panel 3.5mm jack has been included for connection to any standard MP3 player's earphone output.

FEATURES:

- Two XLR Microphone Inputs (including a paralleled front panel input)
- Individually switchable phantom power
- Four Stereo Source Inputs, Four RCA and one front panel stereo 3.5mm
- Cue Select Switch -
- Stereo RCA Record Output
- 1/4" TRS Mic Insert jack

SPECIFICATIONS

Input Impedance:	Mic:	600 Ohms XLR balanced
	Source:	22K Ohms RCA
	Mic Insert:	22K Ohms 1/4" TRS insert
Max Input Level:	Mic:	-14 dBV Mic level
	Source:	24 dBV
Headphone Output Impedance:		>8 Ohms
In/Out Connectors:		3: XLR, 5: Stereo RCA, 4: 1/4" TRS, 1: 3.5mm
Phantom Power:		+12 VDC
Output Level:		+17 dBV max
Output Impedance:		51 Ohms
Max Gain:	Mic:	60 dB
	Source:	26 dB
Tone Controls:		+/-12 dB 100 Hz Bass +/-12 dB 11kHz Treble
Noise Floor:		- 80 dB, THD: <.025%,
S/N Ratio:		96 dB
Size:		19" x 1.75" x 4" (48.3 x 4.5 x 10 cm)
Weight:		5 lbs. (2.3 kg)

ROLLS

ROLLS Coporation
5968 South 350 West, Salt Lake City, UT, 84107
(801) 263-9053 FAX (801) 263-9068
info@rolls.com • www.rolls.com